

BLACKSTAR AMPED 3 (100-Watt 3 Channel High Gain Amp Pedal)

• Item: 59083

EAN: 0845644006878

• Packaging Dimensions: 35 x 19 x 14 cm

• Weight: 2.3 kg

• Pictures | Translations | User Manual

Need to know for Retailers

- 100-Watt 3 channel high gain pedal amp
- Perfect for high-gain player normally looking for a multi-channel valve amp
- Power a tradional cabinet, connect directly to the PA with DI Out and cab-sim or record via USB
- Response control delivers 3 distinctly different power valve repsones: EL84, EL34, 6L6
- 3 footswichable channels (Clean, Crunch, Overdrive) with 2 voicings each
- Programable Pre- or Post-Boost with dedicated switch and level control
- Pro-connectivity: XLR DI out, USB audio, FX loop, Phones out & more
- Use Blackstar's CabRig cab-simulation on DI out and USB for live-performances through the PA and recording-applications
- Completes Blackstars new AMPED product-family (AMPED 1, AMPED 2, AMPED 3)
 - o AMPED 1 = 100-Watt Amp with Reverb
 - o AMPED 2 = 100-Watt Amp with comprehensive FX Rig
 - o AMPED 3 = 100-Watt 3-Channel Amp with Boost

Full Feature List

- 100-Watt 3-channel high gain pedal amp
- Power a traditional cabinet or connect directly to the PA via XLR DI Out using CabRig (cab sim)
- 3 footswitchable channels: Clean, Crunch and Overdrive
- 2 selectable voices per channel to dial in the perfect tone
- Response control delivers 3 distinctly different power valve responses: EL84, EL34, 6L6
- Patented ISF (Infinite Shape Feature) tone control for user sound customization
- EQ: Bass, Moddle, Treble, ISF & Presence
- Programmable Pre or Post Boost including level control
- Power reduction down to 20 Watt or 1 Watt
- 2 Reverb modes (dark, light) with Freeze effect
- Presets can be stored and recalled directly from the AMPED 3
- Easy pedalboard integration: FX loop, 2x 9V DC out (500mA combined) and MIDI control
- Blackstar's "CabRig" cabinet simulation technology featuring over 250 editable mic and cab combinations
- Free Architect editor software for CabRig and further deep dive settings on AMPED 3
- Low-latency 4-channel USB audio for recording into your DAW (feat. CabRig)
- XLR DI Output for direct PA applications (feat. CabRig)
- Headphone output (feat. CabRig)
- Small enough to fit in a gig-bag pocket
- Speaker outputs: 8 Ohm, 16 Ohm
- Universal auto-range Power Supply (90V to 264V) to power all over the world
- Accessories included: 2x TRS MIDI to 5 pin MIDI adaptor, USB-C cable
- Designed by Blackstar UK



Short Description

AMPED 3 is a 100 Watt high gain pedal amplifier featuring 6 voicing options and 3 programmable channels with Reverb. Perfect for players seeking the ultra high gain tones found in multi-channel valve amps like Series One. You can use it to power

a cabinet up to 100 Watts, go direct or to use in the front end of a traditional amp ensuring you can take your sound with you anywhere. Power reduction down to 1W and USB-C connectivity means it's equally at home in the studio or the stage.









B2B Download Link (images, manual, ads, white paper, etc.)